
AVAILABILITY

Net metering service is available under this rider at points on the Cooperative's existing electric distribution system, located within its service area, for Customers operating Renewable Energy Resources. The net metering service is available to Customer-generators on a first-come, first-served basis until the total rated generating capability of all net metering interconnections during a calendar year equals or exceeds one percent of the Cooperative's peak load for the previous calendar year. Upon reaching either of these limits no further net metering service shall be available for that calendar year. This rider shall not be available for any electric service schedule allowing for resale. A Customer-generator shall have the alternative option of interconnecting renewable generation under the Cooperative's Renewable Parallel Generation Rider. However, renewable Customer-generators may not change between the net metering and parallel generation riders without the prior approval of the Cooperative, and such elections shall not be for periods less than one year.

APPLICABILITY

This net-metering rider is applicable to Customer-generators with a Cooperative-approved interconnection agreement that are taking service under one of the Cooperative's normal rate schedules. To determine total applicable net metering maximum allowed capacity, see table below.

Officer



Title

PRESIDENT

For Bills Rendered on or after May 1, 2020

Replacing Schedule 17 - NM

Total Maximum Allowed Capacity (kW)

Customer Type	For customer with approved facilities	
	Operational prior to January 1, 2017	After January 1, 2017
Residential	200 kW	15 kW
General Service	200 kW	100 kW
Large General Service	200 kW	100 kW
Irrigation	200 kW	100 kW
Schools*	200 kW	150 kW

- *The Net Metered Facility shall be appropriately sized for Customer's anticipated electric load. Cooperative will work with Customer to determine appropriately sized units, based on historical load profiles of Customer's operations at point of interconnection.*
- *Any post-secondary educational institution as defined in KSA 74-3201b, and amendments thereto, or any public or private school which provides instruction for students in kindergarten through 12.*
- *Customer-generators with a net metered facility operational prior to January 1, 2017, covered by this Rider may install additional renewable energy resource after that date, as long as the pre-date maximum limits are observed. Maximums listed for before and after the date are not additive.*

CHARACTER OF SERVICE

Alternating current, 60 cycles, at the voltage and phase of the Cooperative's established secondary distribution system immediately adjacent to the service location.

BILLING AND PAYMENT

The Cooperative shall render a bill for net consumption at approximately 30-day intervals during the Cooperative's normal billing process.

Officer Walter Bauer Title PRESIDENT

For Bills Rendered on or after May 1, 2020

Replacing Schedule 17 - NM

=====
The Grid-Use Charge is designed to recover the Cooperative's cost associated with owning and maintaining the distribution and transmission facilities required to provide reliable electric service when the Customer-generator cannot meet its own supply needs.

Any renewable Customer-generators with installed and operating generation prior to January 1, 2017, shall be grandfathered in and the Grid-Use Charge waived until such time as the Customer modifies the nameplate capacity or type of generation.


A Customer-generator, which installs renewable generation on or after January 1, 2017, shall be billed a monthly Grid-Use Charge, based on a per kW of nameplate generating capability as defined herein and that may be updated and amended from time to time by the Board of Trustees.

- Residential \$2.98 per kW per month
- General Service \$4.43 per kW per month
- Large General Service \$7.03 per kW per month
- Irrigation \$2.46 per kW per month

Net consumption is defined as the kWh supplied by the Cooperative to the Customer-generator minus kWh supplied by the Customer-generator and returned to the Cooperative's grid during the billing period. Any net consumption shall be valued as follows:

To the extent the net consumption is positive (i.e. Customer-generator took more kWh from the Cooperative during the billing period than Customer-generator produced), the eligible Customer-generator will be billed in accordance with the Cooperative's standard rate for Energy Charges (for the net consumption), and for any Customer Charges, Demand Charges, and/or any Minimum Charges that would otherwise be applicable to the Customer under the standard rate plus the applicable Grid-Use Charge.

=====
Officer



Title

PRESIDENT

For Bills Rendered on or after May 1, 2020

Replacing Schedule 17 - NM

=====

To the extent the net consumption is negative (i.e. Customer-generator produced more kWh during the billing period than the Cooperative supplied), the Customer-generator will pay applicable Grid-Use Charge, Customer Charges, Demand Charges, or all, depending upon the Cooperative's standard rate applicable to the Customer; and the excess electric energy shall be retained by the Cooperative as a contribution to fixed costs associated with owning and maintaining the facilities required to provide electric service when the Customer-generator cannot meet its own supply needs.

To the extent the net consumption is zero (i.e. the Customer-generator produced the same kWh during the billing period as was supplied by the Cooperative), the Customer generator will be billed in accordance with the Cooperative's otherwise applicable standard rate for the eligible Customer-generator, including any applicable Customer Charges, Demand Charges and/or Minimum Charges and the Grid-Use Charge.

DEFINITIONS

Customer-generator:

The owner or operator of a qualified electric energy generation unit which:

- (a) Is powered by a Renewable Energy Resource as defined by Kansas state statutes (see definition below);
- (b) Has an electrical generating capacity of not more than total maximum capacity;
- (c) Is located on a premises owned, operated, leased, or otherwise controlled by the Customer-generator;
- (d) Is interconnected and operates in parallel phase and synchronization with the Cooperative;
- (e) Is intended primarily to offset part or all of the Customer-generator's own electrical energy requirements;
- (f) Meets all applicable safety, performance, interconnection, and reliability standards established by the National Electrical Code, the National Electrical Safety Code, the Institute of Electrical and Electronics Engineers, Underwriters Laboratories, the Federal Energy Regulatory Commission, and any local governing authorities; and
- (g) Contains a mechanism that automatically disables the unit and interrupts the flow of electricity back onto the Cooperative's electric lines in the event that service to the

=====

Officer



Title

PRESIDENT

For Bills Rendered on or after May 1, 2020

Replacing Schedule 17 - NM

Customer-generator is interrupted.

Each meter connected under this Net Metering Rider defines a Customer-generator. A generator owned or operated by a Customer-generator cannot be connected in common with any other meter or be deemed to be for the purpose of serving the load connected to any other meter. To the extent that the Customer-generator controls the Renewable Energy Resources and meets the requirements and accepts all of the obligations of this Net Metering Rider, the Customer-generator is not required to own the generating facilities.

Renewable Energy Resources:

Electrical energy produced from an energy resource or technologies defined as renewable in K.S.A. 17-4652, and amendments thereto, and energy produced from municipal or other solid waste and animal waste.

Net metering:

A bi-directional metering process using equipment sufficient to measure the difference between the electrical energy supplied to a Customer-generator by Cooperative and the electrical energy supplied by the Customer-generator to the Cooperative over an applicable billing period.

Peak load:

The one-hour maximum annual demand imposed by the Cooperative's retail load applicable to the territory to which this schedule is applicable.

TERMS AND CONDITIONS

1. The Cooperative will supply, own and maintain at its expense all necessary meters and associated equipment utilized for billing. In addition, and for purposes of monitoring Customer generation and load, the Cooperative may install load research metering at its expense. The Customer shall supply, at no expense to the Cooperative, a suitable location for meters and associated equipment used for billing and for load research. Such equipment shall be accessible at all times to Cooperative personnel.

Officer



Title

PRESIDENT

For Bills Rendered on or after May 1, 2020

Replacing Schedule 17 - NM

-
2. The Cooperative shall have the right to require the Customer, at certain times and as electric operating conditions warrant, to limit the production of electrical energy from the generating facility to an amount no greater than the load at the Customer's facility of which the generating facility is a part.
 3. The Customer shall furnish, install, operate and maintain in good order and repair without cost to the Cooperative such relays, locks and seals, breakers, automatic synchronizers, disconnecting devices, and other control and protective devices as shall be designated by the Cooperative as being required as suitable for the operation of the generator in parallel with the Cooperative's system.
 4. The Customer shall install and maintain a visible, manual disconnect switch. This manual switch must have the capability to be locked out by Cooperative personnel to isolate the Cooperative's facilities in the event of an electrical outage on the Cooperative's transmission and distribution facilities serving the Customer. This isolating device shall also serve as a means of isolation for the Customer's equipment during any Customer maintenance activities, routine outages or emergencies. The Cooperative shall give notice to the Customer before a manual switch is locked or an isolating device used, if possible; and otherwise shall give notice as soon as practicable after locking or isolating the Customer's facilities.
 5. The Customer shall reimburse the Cooperative for any equipment, facilities, protective equipment or upgrades required solely as a result of the installation by the Customer of generation in parallel with the Cooperative's system.
 6. The Customer shall notify the Cooperative prior to the initial energizing and start-up testing of the Customer-owned generator, and the Cooperative shall have the right to have a representative present at said test.
 7. If harmonics, voltage fluctuations, or other disruptive problems on the Cooperative's system are directly attributable to the operation of the Customer's system, such problem(s) shall be corrected at the Customer's expense.

Officer

Will Bane

Title


PRESIDENT

For Bills Rendered on or after May 1, 2020

Replacing Schedule 17 - NM

-
8. No Customer's generating system shall damage the Cooperative's system or equipment or present an undue hazard to Cooperative personnel. The Cooperative shall not be liable directly or indirectly for permitting or continuing to allow an attachment of a net metered facility or for the acts or omissions of a Customer-generator that cause loss or injury, including death, to any third party. The Customer-generator agrees to hold the Cooperative harmless from injury or property damage incurred by any person and arising out of the ownership, operation, maintenance, or use of the Customer's electrical generation facility and to indemnify the Cooperative against all liability and expense related thereto.
 9. Prior to installing and interconnecting a Renewable Energy Resource the Customer shall enter into a standard interconnection contract with the Cooperative setting forth the conditions related to technical and safety aspects of parallel generation.
 10. Service under this Net Metering Rider is subject to the Cooperative's Parallel Generation Interconnection Regulations found in the Cooperative's approved rules and regulations and subsequent modifications thereto.
 11. The Customer-generator shall, at its own expense, maintain in force general liability insurance without any exclusion for liabilities related to the interconnection. The amount of such insurance shall be sufficient to insure against all reasonably foreseeable direct liabilities given the size and nature of the generating equipment being interconnected, the interconnection itself and the characteristics of the system to which the interconnection is made. For Renewable Energy Resource systems having a maximum nameplate generating capability of 10 kW or less, a Customer-generator whose system meets the standards specified in Cooperative's Parallel Generation Interconnection Regulations found in the Cooperative's approved rules and regulations shall not be required to install additional controls, perform or pay for additional tests or distribution equipment or purchase additional liability insurance other than such general liability insurance. For Renewable Energy Resource systems having a maximum nameplate generating capability of greater than 10 kW, the Cooperative's Parallel Generation Interconnection Regulations found in the Cooperative's approved rules and regulations shall: (1) Set forth safety, performance and reliability standards and insurance requirements; and (2) establish the qualifications for exemption from a requirement to install additional controls, perform or pay for additional tests or distribution equipment or purchase additional liability insurance.

Officer



Title

PRESIDENT

For Bills Rendered on or after May 1, 2020

Replacing Schedule 17 - NM

-
12. Applications by a Customer-generator for interconnection of the qualified generation unit to the distribution system shall be accompanied by the plan for the Customer-generator's electrical generating system, including, but not limited to, a wiring diagram and specifications for the generating unit, and shall be reviewed and responded to by the Cooperative within 30 days after receipt for systems of 10 kilowatts or less and within 90 days after receipt for all other systems. Prior to the interconnection of the qualified generation unit to the Cooperative's system, the Customer-generator shall furnish the Cooperative a certification from a qualified professional electrician or engineer that the installation meets the requirements of Cooperative's Parallel Generation Interconnection Regulations found in the Cooperative's approved rules and regulations. If the application for interconnection is approved by the Cooperative and the Customer-generator does not complete the interconnection within one year after receipt of notice of the approval, the approval shall expire and the Customer-generator shall be responsible for filing a new application. Upon the change in ownership of a qualified Renewable Energy Resource, the new Customer-generator shall be responsible for filing a new application under this section.
13. Ownership of all renewable energy credits, greenhouse gas emission credits or any other renewable energy attributes related to any electricity produced by the eligible renewable energy resource shall be retained by the Customer-generator.

Officer Will Barnes Title PRESIDENT

For Bills Rendered on or after May 1, 2020

Replacing Schedule 17 - NM